

vSpace Client		Supported firmware (vSpace Client) versions								
		L250	L300/L350	M300	MX100S MX100D	vSpace Client for Windows ²	vSpace Client for CX100 Chromebook	L130/L230	X350/X550	U170
vSpace Server for Windows										
vSpace Server 6 (U-series) Version: 6.4.3.7 Windows Server 2008 R2 SP1 Windows MultiPoint Server 2011 Windows 7 SP1 (32- and 64-bit) ¹	-	-	-	-	-	-	-	-	-	✓ ³
vSpace Server 4 (L-series) Version: 4.9.6.1 Windows Server 2003 R2 SP2 (32-bit) Windows XP SP3 ¹ (32-bit)	-	1.4.1 (L300 only)	-	-	-	-	14601/14574	-	-	-
vSpace Server 4 (X-series) Version: 4.4.11.1 Windows Server 2003 R2 SP2 (32-bit) Windows XP SP3 ¹ (32-bit)	-	-	-	-	-	-	-	✓	-	-
vSpace Server 4 (U-series) Version: 4.8.1.26 Windows Server 2003 R2 SP2 (32-bit) Windows XP SP3 ¹ (32-bit)	-	-	-	-	-	-	-	-	-	✓

Supported Windows Server OS versions: Standard, Enterprise and Datacenter

Supported Windows Desktop OS versions: Professional, Business, Enterprise and Ultimate¹

¹ Microsoft Windows Server and appropriate client access licenses are required for multiuser environments using NComputing products. Desktop operating systems such as Microsoft Windows XP, Microsoft Windows Vista, Microsoft Windows 7, and Microsoft Windows 8 are appropriate for single user applications such as 1:1 VDI, display systems, and remote access. Home versions are NOT supported. Additional information on licensing is available at <http://www.ncomputing.com/mslicensing> including frequently asked questions.

² vSpace Client is supported on PCs, laptops and netbooks running Windows XP SP3 (32-bit), Windows 7 SP1 (32- and 64-bit), and Windows 8 as well as Windows Server 2008 R2 SP1, and Windows Multipoint Server 2011.

³ Only supports Server 2008 R2 (non-SP1) and MultiPoint Server 2010 (non-SP1). For MultiPoint Server 2011, driver option is available - see Download Center.

✓ – Client device is supported. X-series and U-series are zero-clients and do not have firmware thus no firmware version is specified.

		Supported firmware (vSpace Client) versions								
		L250	L300/L350	M300	MX100S MX100D	vSpace Client for Windows ²	vSpace Client for CX100 Chromebook	L130/L230	X350/X550	U170
vSpace Client	vSpace Server for Linux									
	vSpace Server for Linux Version: 3.2.2.28 (L-series) Ubuntu Desktop 10.04.4 Ubuntu Desktop 12.04.2 MAX (Madrid Linux) 6.5 MAX (Madrid Linux) 7.0	-	1.6.3 (L300 only)	2.0.54	-	-	-	-	-	-
	vSpace Server for Linux Version: 3.1.5.4 (X-series) Ubuntu Desktop 10.04.3 Version: 3.3.5 (X-series) Ubuntu Desktop 14.04.2 (64-bit)	-	-	-	-	-	-	-	✓	-

✓ – Client device is supported. X-series and U-series are zero-clients and do not have firmware thus no firmware version is specified.

		Supported firmware versions			
		N400	N500	N500w	N600
N-series client	vSpace Management Center				
	vSpace Management Center Version: 3.7.26 (virtual appliance) Citrix XenServer 6.2, 6.5 Microsoft Hyper-V (Windows Server 2008 R2, 2012 R2) VMware ESXi 5.1, 5.5, 6.0	1.6, 2.1, 2.3, 2.4 and 2.6	1.6, 2.1, 2.3, 2.4 and 2.6	1.6, 2.1, 2.3, 2.4 and 2.6	2.6
	vSpace Management Center Version: 3.7.17 (virtual appliance) Citrix XenServer 6.2 Microsoft Hyper-V (Windows Server 2008 R2, 2012 R2) VMware ESXi 5.1	1.6, 2.1, 2.3 and 2.4	1.6, 2.1, 2.3 and 2.4	1.6, 2.1, 2.3 and 2.4	–